

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

## Class II FSP Switchgear Assembly (Type: FSP01 and FSP02)

### Product Description

Class II FSP Switchgear Assembly (Type: FSP01 and FSP02) for Signalling Power Supplies

### Typical Product Image



### Scope of Acceptance

#### Full Acceptance

Full acceptance as per the User and Manufacturer's conditions detailed within this certificate.

Network Rail Acceptance Panel (NRAP) hereby authorises the product above for use and trial use on railway infrastructure for which Network Rail is the Infrastructure Manager under the ROGS regulations.

Reviewed by:

Authorised by:



Tom Riley  
Product Acceptance Coordinator



Kyle Windsor  
Acting Professional Head of Power Distribution HV/LV

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

## Specific Conditions

*The following Conditions are specific to the approved product/s contained within this Certificate. These conditions must be adhered to in addition to the Network Rail General Conditions contained within the "General Terms and Conditions" section.*

*Failure to adhere to these conditions may result in the withdrawal or suspension of Acceptance of some, or all of the items contained within the accepted configuration.*

### Manufacturer

- 1) The Class II 'Power Block' production units shall be tested in accordance with section 4.5.2 of NR/L2/SIGELP/27409 (Class II dielectric test). Test records along with photos for each production unit shall be maintained for traceability of Class II tests.
- 2) In addition the Class II 'Power Block' production units shall be tested in accordance with Inspection & Test Report Class II rev3 and Mechanical Test Report 2.0. All Testing shall be conducted as per Inspection & Test Procedure ILS100023 rev2.3.
- 3) All Class II 'Power Block Compact' production units shall be tested in accordance with section 4.5.2 of NR/L2/SIGELP/27409 (Class II dielectric test). Test records along with photos for each production unit shall be maintained for traceability of Class II tests.
- 4) All Class II 'Power Block Compact' production units shall be tested in accordance with ILS100042 Inspection & Test Report Class II rev2.3 and ILS100042 Mechanical Test Report rev1.1. All testing shall be conducted as per the ILS100042 Test Procedure r2.4.

### User

The Class II 'Power Block' product range is suitable for use as a Class II FSP Switchgear Assembly in accordance with NR/L2/SIGELP/27409.

Where Class II 'Power Block' is used in Class I installations the continuity of the protective conductors or bonding must be maintained.

Note: The use of Class II Switchgear Assemblies alone in Class I installations does not provide full protective measures as detailed in NR/L2/SIGELP/27410.

The following application criteria and installation constraints shall be complied with:

- 1) A Class II installation is satisfied if the Class II 'Power Block' is installed in conjunction with other system components in accordance with NR/L2/SIGELP/27410.
- 2) Only for use as categories FSP01 and FSP02 in accordance with NR/L2/SIGELP/27409.
- 3) Use limited to a single end fed radial system (or branch from the main distribution system) (FSP 01 & FSP02); manual reconfiguration dual end fed system (FSP02).
- 4) FSP Switchgear Assemblies for use with 2 core cable in accordance with NR/L2/SIGELP/27408 or unarmoured B2/D2 EPR cable to NR/PS/SIG/00005 or other legacy 2 core unarmoured cable.
- 5) Functional circuit protection feeding transformers shall be in accordance with approved transformer manufacturer recommendations. The use of MCB or MCCB over current protective devices in the switchgear assembly will require a product change request in accordance with Application For Configuration Change Or Update.
- 6) Not to be used in subsurface environments in accordance with section 12 stations and locations.
- 7) The Class II 'Power Block' shall not be installed in signalling distribution feeders, where the PSP outgoing or source feeder protection exceeds a BS 88 63A at AC22 or equivalent protective device.
- 8) Where Overvoltage protection is specified or fitted it shall be a Product Approved 2 Wire Overvoltage protection device in accordance with NR/L2/SIGELP/27410.
- 9) Class II 'Power Block' properties suitable for installation in marine/aggressive applications.
- 10) Where Class II 'Power Block' is damaged externally and requires repair in accordance with the O&M manual, this shall be undertaken by the original manufacturer.





**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

- 11) Class II FSP Switchgear Assemblies shall not be drilled on site. Brass glands (Metallic) shall only be used with fully Insulated Adaptor Reducer, with a dielectric strength exceeding 3.5KV, in accordance with NR/L2/SIGELP/27410.
- 12) Class II FSP Switchgear Assembly (Type: FSP01 and FSP02)–ABB E90 series IEC 60269 Fuse holders shall only be used in conjunction with Signalling Transformers in accordance with NR/L2/SIGELP/30007 and shall not be used to connect to Signalling transformers in accordance with BR924A.
- 13) Power Block Compact 300 is limited to a maximum feeder cable size of 35mm<sup>2</sup> Copper (Cu) cable.
- 14) Power Block Compact 400 is limited to a maximum feeder cable size of 120mm<sup>2</sup> Copper (Cu) cable.


## Product Configuration: Issue 5

### Class II FSP Switchgear Assembly (Type: FSP01 and FSP02)–CAMaster BS88 Fuse-holders




Part Number	Distribution Switches	Functional Switches	Auxiliary Switches	Fuses	Drawing Ref/ Image	Catalogue Number
PL-CII/1SW-SL	2	1	0	2	170112-020	054/213850
	<b>Power Block 1 switch, Single Layer without ESP</b>					
Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. One switched & fused output functional supply. Fuse-carriers to be BS88 (CAMaster).						
PL-CII/2SW-SL	2	2	0	4	02-21-129	054/213851
	<b>Power Block 2 switch, Single Layer without ESP</b>					
Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Two switched & fused output functional supplies. Fuse-carriers to be BS88 (CAMaster).						
PL-CII/2SW-ESP-SL	2	2	0	4	170327-348	054/213852
	<b>Power Block 2 switch, Single Layer with ESP</b>					
Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Two switched & fused output functional supplies. One switched & fused internal supply to Surge Arrestor. Built-in Surge Arrestor. Fuse-carriers to be BS88 (CAMaster).						
PL-CII/3SW-SL	2	3	0	6	03-12-585	054/213853
	<b>Power Block 3 switch, Single Layer without ESP</b>					
Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Three switched & fused output functional supplies. Fuse-carriers to be BS88 (CAMaster).						

Manufacturer:  
ILECSYS Ltd

Issue : 6  
Valid From : 29/03/2018

Part Number	Distribution Switches	Functional Switches	Auxiliary Switches	Fuses	Drawing Ref/ Image	Catalogue Number
	2	3	0	6	02-20-314	
<b>PL-CII/3SW-ESP-SL</b>	<b>Power Block 3 switch, Single Layer with ESP</b>					054/213854
	Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Three switched & fused output functional supplies. One switched & fused internal supply to Surge Arrestor. Built-in Surge Arrestor. Fuse-carriers to be BS88 (CAMaster).					

**Class II FSP Switchgear Assembly (Type: FSP01 and FSP02)–ABB E90 series IEC 60269 Fuse-holders**

Part Number	Distribution Switches	Functional Switches	Auxiliary Switches	Fuses	Drawing Ref/ Image	Catalogue Number
	2	1	0	2	03-24-403	
<b>PL-CII/1SW-SL-IEC</b>	<b>Power Block 1 switch, Single Layer without ESP</b>					054/213855
	Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. One switched & fused output functional supply. Fuse-carriers to be IEC 60269 (ABB)					
	2	2	0	4	02-22-083	
<b>PL-CII/2SW-SL-IEC</b>	<b>Power Block 2 switch, Single Layer without ESP</b>					054/213856
	Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Two switched & fused output functional supplies. Fuse-carriers to be IEC 60269 (ABB)					
	2	3	0	6	03-10-248	
<b>PL-CII/3SW-SL-IEC</b>	<b>Power Block 3 switch, Single Layer without ESP</b>					054/213857
	Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Three switched & fused output functional supplies. Fuse-carriers to be IEC 60269 (ABB)					



**Hardware (Maintenance Spares and Line Replaceable Units)**

Part No.	Description	Image	Catalogue No.
--	E 91/32 Fuse-disconnector for 10.3 x 38mm fuses		054/213860

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

**Class II FSP Switchgear Assembly (Type: FSP01 and FSP02) – Compact Range**




<p><b>PL-CII/3SW-SLC-35</b></p>	2	3	0	6	<b>03-28-560</b>	<p><b>054/213858</b></p>
	<p><b>Power Block Compact 300, 3 switch, Single Layer without ESP</b></p> <p>Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Three switched &amp; fused output functional supply. Fuse-carriers to be IEC 60269 (ABB). Switchgear height 300mm</p>					
<p><b>PL-CII/3SW-SLC-120</b></p>	2	3	0	6	<b>03-21-348</b>	<p><b>054/213859</b></p>
	<p><b>Power Block Compact 400, 3 switch, Single Layer without ESP</b></p> <p>Class II distribution unit rated to 690V fitted with Ring Power IN and OUT Isolators. Three switched &amp; fused output functional supplies. Fuse-carriers to be IEC 60269 (ABB). Switchgear height 400mm</p>					

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018



## Product Configuration: Issue 6 - Additional Switchgear Assembly Modules

### System or Complete Assembly

Part Number	Distribution Switches	Functional Switches	Auxiliary Switches	Fuses	Drawing Ref/ Image	Catalogue Number
PL-CII/6SW-SLC-001	1	6	0	12	171201-1363	
	<b>FSP-01 Single End Fed Switch Box - 6SW Functional Supply</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm) Suitable for Copper (Cu) 2C feeder cables</li> <li>• Cable size &gt;35mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 600 x 300 x 275</li> <li>• Weight - 19kg</li> </ul>					054/213865
	2	6	0	12	170330-377	
PL-CII/6SW-SLC-2B	<b>FSP-02 Dual End Fed Switch Box - 6SW Functional Supply</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Suitable for Copper (Cu) 2C feeder cables Cable size &gt;35mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 600 x 300 x 275</li> <li>• Weight - 19kg</li> </ul>					054/213866
	1	6	0	12	03-19-100	
PL-CII/6SW-SLC-ESP/ABB	<b>FSP-01 Single End Fed Switch Box - 6SW Functional Supply with ESP</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Supplied with ESP</li> <li>• Suitable for Copper (Cu) 2C feeder cables</li> <li>• Cable size &gt;35mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 600 x 300 x 275</li> <li>• Weight – 19kg</li> </ul>					054/213867




Manufacturer:  
ILECSYS Ltd

Issue : 6  
Valid From : 29/03/2018

Part Number	Distribution Switches	Functional Switches	Auxiliary Switches	Fuses	Drawing Ref/ Image	Catalogue Number
PL-CII/3SW-SLC-ESP-120	2	3	0	6	180130-083	054/213868
	<b>FSP-02 Dual End Fed Manually Reconfigurable Switch Box - 2 Functional Switches with ESP</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Supplied with ESP</li> <li>• Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>• Cable size 16-120mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 400 x 400 x 275 (496W x 435H including mounting bracket)</li> <li>• Weight – 12kg</li> </ul>					
PL-CII/3SW-SL-IEC120-A-ESP	2	3	0	6	160407-310	054/213869
	<b>FSP-02 Dual End Fed Manually Reconfigurable Switch Box - 2 Functional Switches with ESP &amp; 650V Spur Switch</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Supplied with ESP</li> <li>• Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>• Cable size 16-120mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 400 x 400 x 275 (496W x 435H including mounting bracket)</li> <li>• Weight - 12kg</li> <li>• One Functional Supply with one 650V Spur cable size up to 120mm Cu/Al</li> </ul>					

**Manufacturer:**  
ILECSYS Ltd



**Issue :** 6  
**Valid From :** 29/03/2018

<p><b>PL-CII/4SW-SLC-IEC120</b></p>	2	4	0	8	<p><b>160915-835</b></p> 	<p><b>054/213870</b></p>
	<p><b>Dual End Fed Manually Reconfigurable Switch Box - 4 Functional Switches</b></p> <ul style="list-style-type: none"> <li>Isolation and distribution enclosure for 650V signalling systems, rated current 63A</li> <li>Full Class II specification.</li> <li>Assembly insulation dielectric strength certified to 10kV</li> <li>Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>Cable size 120mm<sup>2</sup></li> <li>Dimensions [(W x H x D) mm] - 400 x 400 x 275</li> <li>Weight – 12kg</li> </ul>					
<p><b>PL-CII/4SW-SLC-IEC120-ESP</b></p>	2	3	1	8	<p><b>151023-748</b></p> 	<p><b>054/213871</b></p>
	<p><b>Dual End Fed Manually Reconfigurable Switch Box - 3 Functional Switches with ESP</b></p> <p>Isolation and distribution enclosure for 650V signalling systems, rated current 63A</p> <ul style="list-style-type: none"> <li>Full Class II specification. Assembly insulation dielectric strength certified to 10kV</li> <li>Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>Supplied with ESP</li> <li>Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>Cable size 120mm<sup>2</sup></li> <li>Dimensions [(W x H x D) mm] - 400 x 400 x 275</li> <li>Weight – 12kg</li> </ul>					
<p><b>PL-CII/4SW-SLC-IEC-120-ESP-K4C</b></p>	2	3	1	8	<p><b>180220-149</b></p> 	<p><b>054/213872</b></p>
	<p><b>Dual End Fed Manually Reconfigurable Switch Box - 3 Functional Switches with ESP</b></p> <p>Isolation and distribution enclosure for 650V signalling systems, rated current 63A</p> <ul style="list-style-type: none"> <li>Full Class II specification.</li> <li>Assembly insulation dielectric strength certified to 10kV</li> <li>Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>Supplied with ESP</li> <li>Suitable for Aluminium (Al) or Copper (Cu) 2/4C feeder cables.</li> <li>Cable size 16 - 120mm<sup>2</sup></li> <li>Weight – 19kg</li> </ul>					





**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

Part Number	Distribution Switches	Functional Switches	Auxiliary Switches	Fuses	Drawing Ref/ Image	Catalogue Number
FSP01/2S W-SL- IEC/ESP- 95	1	2	0	4	170217-162	054/213873
	<b>FSP-01 / 04 Single End Fed Manually Reconfigurable Switch Box - 2 Functional Switches with ESP</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Supplied with ESP</li> <li>• Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>• Cable size 16-95mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 300 x 300 x 225</li> <li>• Weight – 8kg</li> <li>• One transformer functional supply (SWA)</li> <li>• Suitable for use with single end fed feeder</li> </ul>					
FSP01/2S W-SL- IEC/ESP- 120	1	2	0	4	170217-163	054/213874
	<b>FSP-01 / 04 Single End Fed Manually Reconfigurable Switch Box - 2 Functional Switches with ESP</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Supplied with ESP</li> <li>• Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>• Cable size 35-120mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 300 x 300 x 225</li> <li>• Weight - 9kg</li> <li>• One transformer functional supply (SWA)</li> <li>• Suitable for use with single end fed feeder</li> </ul>					


Manufacturer:  
ILECSYS Ltd

Issue : 6  
Valid From : 29/03/2018

Part Number	Distribution Switches	Functional Switches	Auxiliary Switches	Fuses	Drawing Ref/ Image	Catalogue Number
PL-CII/2SW-SL-IEC/ESP-95/RING	2	2	0	4	170217-164	054/213875
	<b>FSP-02 Dual End Fed Manually Reconfigurable Switch Box - 2 Functional Switches with ESP</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Supplied with ESP</li> <li>• Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>• Cable size 16-95mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 300 x 300 x 225</li> <li>• Weight - 8kg</li> <li>• One transformer functional supply (SWA)</li> <li>• Suitable for use with dual end fed feeder</li> </ul>					
PL-CII/2SW-SL-IEC/ESP-120/RING	2	2	0	6	170217-165	054/213876
	<b>FSP-02 Dual End Fed Manually Reconfigurable Switch Box - 2 Functional Switches with ESP</b> Isolation and distribution enclosure for 650V signalling systems, rated current 63A <ul style="list-style-type: none"> <li>• Full Class II specification.</li> <li>• Assembly insulation dielectric strength certified to 10kV</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• Supplied with ESP</li> <li>• Suitable for copper (Cu) or aluminium (Al) 2C feeder cables.</li> <li>• Cable size 35-120mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 300 x 300 x 225</li> <li>• Weight - 9kg</li> <li>• One transformer functional supply (SWA)</li> <li>• Suitable for use with dual end fed feeder</li> </ul>					

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

<b>ILS100047 /299</b>	0	1	1	4	<b>170613-639</b>		<b>054/213877</b>
	<b>FSP01 Complete with ESP and Earth Connection Box (ECB) Assembly</b> <ul style="list-style-type: none"> <li>• Suitable for the fast and efficient upgrade of 'Legacy' location cases or new installations</li> <li>• Class II distribution unit(FSP04) rated to 690V fitted with 63A line isolator</li> <li>• Functional supply fuse carriers - ABB IEC60269 (10x38mm)</li> <li>• One switched and fused output functional supply</li> <li>• ECB box suitable for the termination of 3 core armoured cable to retain the Class II integrity of the FSP04</li> <li>• Cable size 16-95mm<sup>2</sup></li> <li>• Dimensions [(W x H x D) mm] - 200 x 500 x 225</li> <li>• Weight - 10kg</li> <li>• Front cover hinged on left hand side</li> </ul>						

## Assessed Documentation

Reference	Title	Doc. Rev.	Date and Applies to Cert. issue No.	
	PA05/05344 Evidence zip file (Contains NR & iLecsys Folders)		02/01/2013	1
ILS100023	PA05/05344 Acceptance Requirements Response (Cover Letter)		undated	1
NR/SE/AR/CII	PA05/05344 Sponsors Report		12.12.2012	1
ILS100023	PA05/05344 Appendix Directory (NR & iLecsys)		19.11.2012	1
ILS100023	Compliance Matrix to NR/L2/ELP/27409		15.11.2012	1
ILS100023	Compliance Matrix to BS 7671(Extract)		15.11.2012	1
ILS100023	Compliance Matrix to BS EN 61439 (Extract)		15.11.2012	1
-	Certificates folder		02/01/2013	1
-	Components (Data Sheets) folder		02/01/2013	1
-	Reports folder		02/01/2013	1
-	Supporting Documents folder		02/01/2013	1

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

Reference	Title	Doc. Rev.	Date and Applies to Cert. issue No.	
-	Drawings (GA & Wirings) folder		02/01/2013	1
ILS100023_PA05/5344	O&M Manual Version 1.7		09/01/2013	1
-	Images/Photographs		02/01/2013	1
-	Test Data (Additional Videos)		02/01/2013	1
-	iLecsys Test Reports Covering Letter		14.12.2012	1
19056	ISO9001:2008 certificate		20.07.2011	1
	Link up Certificate		08.01.2013	1
	PA05/05344/1 Evidence zip file (Contains iLecsys Change Evidence Folders)		08/07/13	2
	PA05/05344/1 Application for Configuration Change		08/07/13	2
	PA05/05344/2 Evidence zip file (Contains iLecsys Change Evidence Folders)		14/04/2014	4
	PA05/05344/2 Application for Configuration Change		11/07/2013	4
03-15-129 iss B	Schematic	Iss B	29/03/2018	6
03-19-100 iss B	GA Drawing	Iss B	29/03/2018	6
151023-748 iss B	GA Drawing		29/03/2018	6
151113-813 iss A	Schematic		29/03/2018	6
160407-310 iss A	GA Drawing		29/03/2018	6
160915-835 iss A	GA Drawing		29/03/2018	6
160915-838 iss A	Schematic		29/03/2018	6
170217-162 iss A	GA Drawing		29/03/2018	6
170217-163 iss A	GA Drawing		29/03/2018	6
170217-164 iss A	GA Drawing		29/03/2018	6
170217-165 iss A	GA Drawing		29/03/2018	6
170323-331 iss A	Schematic		29/03/2018	6
170330-377 iss B	GA Drawing		29/03/2018	6
170421-464-01 iss A	Schematic		29/03/2018	6
170613-639 iss C	GA Drawing		29/03/2018	6
170821-910 iss A	Schematic		29/03/2018	6
170821-911 iss A	Schematic		29/03/2018	6
170822-919 iss A	Schematic		29/03/2018	6
170822-920 iss A	Schematic		29/03/2018	6
170822-923 iss A	Schematic		29/03/2018	6
171201-1363 iss A	GA Drawing		29/03/2018	6
180130-083 iss A	GA Drawing		29/03/2018	6
O&M ILS100042	O&M Manual - Compact Class II Power Block Single Layer	v1.5	29/03/2018	6
ILS100042 6SW	OM Manual for 6 SW Assemblies	v1.1	29/03/2018	6
Engineering case	Engineering Case for change		29/03/2018	
Safety case	Safety Case for change		29/03/2018	6
Siemens Product Guide	Product configuration guide	_v7.0	29/03/2018	6

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

## Manuals and Training Materials

Reference	Title	Doc. Rev.	Date and Applies to Cert. issue No.	
ILS100023_PA05/05344	O&M Manual	1.6	09/01/2013	1
ILS100042_PA05/05344	O&M Manual	1.4	14/04/2014	4
O&M ILS100042	O&M Manual - Compact Class II Power Block Single Layer	v1.5	29/03/2018	6
ILS100042 6SW	OM Manual for 6 SW Assemblies	v1.1	29/03/2018	6

## Certificate History

Issue	Date	Issue History
1	04/07/2013	First accepted for use
2	12/07/2013	Amended to include new components and new scope of acceptance as per configuration change request PA05/05344/1
3	27/08/2013	Scope of acceptance amended.
4	11/05/2014	Amended to include new configurations and new scope of acceptance as per configuration change request PA05/05344/2
5	09/10/2014	Amended to include 91/32 Fuse-disconnector for 10.3 x 38mm fuses
6	29/03/2018	Amended to include new switch assembly configurations and additional earth connection boxes

## Contact Details

### Manufacturer

Peter Dickson  
Engineering Manager  
iLECSYS Rail Ltd

+ 44 (0) 7720 848089  
[pjd@ilecsys.co.uk](mailto:pjd@ilecsys.co.uk)

### Applicant

Mick Turner  
Principal Engineer  
Infrastructure Projects  
Network Rail

+ 44 (0) 7720 848089  
[Mick.Turner2@networkrail.co.uk](mailto:Mick.Turner2@networkrail.co.uk)

### Lead Reviewing Engineer

Simba Masvaure  
Engineer  
Distribution – STE  
Network Rail

+ 44 (0) 7497 391918  
[Simba.Masvaure@networkrail.co.uk](mailto:Simba.Masvaure@networkrail.co.uk)

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

## General Terms & Conditions

### 1) General

- 1) This certificate can only be amended by Network Rail Product Acceptance, the Professional Head or nominated delegate. Any alterations made by a other persons will invalidate the entire certificate.
- 2) Failure to abide by the requirements in this Certificate of Acceptance may invalidate the certificate, thereby restricting the right to operate the product and / or limiting the future supply and deployment of the product on the infrastructure.
- 3) Upon the review date this certificate and the product it relates to is invalid and not accepted for use. Manufacturers are to make an application for a review prior to the review date.

### 2) Manufacturer

The Manufacturer shall:

- 1) Ensure that all products supplied comply with the standards defined in the Acceptance Requirements or otherwise documented as part of the assessment, including meeting the reliability requirements included in the Acceptance Requirements and in any deed of warranty for the relevant certificate number.
- 2) Notify Network Rail Product Acceptance:
  - a. Within 48 hours, of any deficiencies affecting the quality, functionality or safety integrity of the product (including corrective action undertaken or proposed).
  - b. Of any intended change to the accepted product; changes include:
    - i. a change to the product configuration (to the actual product or its application);
    - ii. a variation to or addition of manufacturing locations or processes;
    - iii. a change in the name or ownership of the manufacturing company;
    - iv. any changes to the ability or intention to support with technical services, spares or repairs.
- 3) The Manufacturer shall provide Network Rail Product Acceptance or National Supply Chain (NSC) at least 12 (twelve) months notice of its intention to discontinue supply or to provide such notice as is reasonable if such discontinuance is outside its control and will offer the opportunity of a Last Time Buy to Network Rail together with date for last order placement and supply of the parts affected. The introduction of proposed alternative products shall be communicated to Network Rail Product Acceptance.
- 4) Provide further copies of operating and maintenance manuals to purchasers / users of the product as necessary (including certificates of conformance, calibration etc).
- 5) Provide further copies of training manuals and an appropriate level of training to purchasers or users of the product as necessary.
- 6) Where applicable, specialist technical support, repairs and servicing of the product shall be carried out by the Original Equipment Manufacturer (OEM) or authorised agent only.
- 7) Network Rail may request information from the manufacturer to prove product compliance with clauses 1 and 2 above and reserve the right to suspend and/or withdraw any application where information is not forthcoming within a reasonable timeframe.
- 8) In accordance with Network Rail's Quality Assurance Policy Statement 2011, where the specification and/or Product Acceptance Certificates specify quality assurance classifications (QA1 to QA5) for the products, the manufacturer shall comply with the specified level of quality assurance for each product and allow Network Rail access to carry out its quality assurance checks.
- 9) The manufacturer shall give Network Rail's representatives access at all reasonable times to its premises and allow them to inspect its quality systems and production methods and, if requested, to inspect, examine and test the products both during and after their manufacture and the materials being used in their manufacture.

### 3) Conditions of Use

Specifiers, installers, operators, maintainers, etc. using the product shall:

- 1) Comply with the certificate conditions. If a condition is not understood guidance must be sought from Network Rail Product Acceptance.
- 2) Check that the application of use complies with the relevant certificate's scope of acceptance.
- 3) Report any defect if it is a design or manufacturing fault likely to affect performance and/or the safe operation of the railway in writing to Network Rail Product Acceptance.
- 4) Inform Network Rail Product Acceptance in writing of a change to the product configuration (or to the actual product or its application).
- 5) Operate, maintain and service the product in accordance with Network Rail standards and Operation and Maintenance manuals as appropriate.
- 6) Be appropriately trained and authorised for the installation, maintenance and use of the product.
- 7) Only send products for repair or reconditioning to the Original Equipment Manufacturer (OEM) or authorised agent.
- 8) Users are to be aware that Product Acceptance is not a substitute for design approval.

**Manufacturer:**  
ILECSYS Ltd

**Issue :** 6  
**Valid From :** 29/03/2018

#### 4) Compliance

Railways and Other Guided Systems (ROGS) Regulations

- 1) Where the product is to be used in areas where Network Rail is not the Infrastructure Manager (e.g. leased stations), the sponsor shall additionally obtain formal consent from the Infrastructure Manager for the locality where the equipment is to be installed. This may include a requirement for additional safety verification. The decision of that Infrastructure Manager is binding, and cannot be overridden by Network Rail except by the escalation processes established in the ROGS regulations
- 2) As required in Railway Group Standard GE/RT8270, at each use of this product the project or group responsible for installation and commissioning shall be required to demonstrate compatibility with:

- a. All rail vehicle types that have access rights over the area affected by the change
- b. Infrastructure managed by others
- c. Neighbours.

Railway Interoperability Regulations

- 3) For interoperable constituents of systems the project or group responsible for installation and commissioning shall be required to demonstrate compliance with the relevant Technical Specifications for Interoperability (TSI) where appropriate.
- 4) An authorisation from the national safety authority (i.e. the Railway Safety Directorate of the Office of Rail Regulation) is required before the equipment is to be used in revenue earning service.

#### 5) Supply Chain Arrangements

- 1) Certificates of acceptance do not imply any particular quantity of supply nor any exclusivity of supply.
- 2) Products may be purchased by Network Rail or its agents, suppliers or contractors.
- 3) Manufacturers should note that it is not necessary to enter into any exclusive supply arrangements with resellers or other suppliers.